



TECHNICAL UNIVERSITY OF MOMBASA

FACULTY OF ENGINEERING AND TECHNOLOGY

DEPARTMENT OF MEDICAL ENGINEERING

UNIVERSITY EXAMINATION FOR:

DIPLOMA IN MEDICAL ENGINEERING

EEP 2251: ELECTRICAL MACHINES AND UTILIZATION II

END OF SEMESTER EXAMINATION

SERIES: Select series 2017

TIME: 2 HOURS

DATE: 2 Sep 2017

Instructions to Candidates

You should have the following for this examination

-Answer Booklet, examination pass and student ID

This paper consists of **FIVE** questions.

Attempt question ONE (Compulsory) and any other TWO questions.

Do not write on the question paper.

Question ONE

a) Describe the following distribution systems:

i). 3-wire

ii). 4-wire

iii). 5-wire

(6 marks)

b) Three identical resistors each of value 52Ω are connected first in star and then in delta across a 415V, 3-phase, 50Hz supply. Calculate:

i). the line current

ii). the phase current

iii). the power taken from the supply in each case.

(14 marks)

- c) If one resistor in (b) is taken out of the circuit in each case, calculate the new values of line and phase currents. **(10 marks)**

Question TWO

- a) State:
- any **ONE** method used to vary the speed of 3-phase induction motors.
 - the effect of interchanging any two phase-lines supplying a 3-phase induction motor. **(2 marks)**
- b) Describe the following types of 3-phase induction motors:
- wound-rotor motor
 - squirrel-cage motor **(4 marks)**
- c) A 3-phase induction motor is wound for 4 poles and is supplied from a 50Hz system. Calculate:
- the synchronous speed
 - the speed of the rotor when the slip is 4% **(6 marks)**
- d) Explain the star-delta method of starting 3-phase induction motors. **(8 marks)**

Question THREE

- a) Define “synchronous speed”. **(1 mark)**
- b) State any **TWO** characteristics of a 3-phase synchronous motor. **(2 marks)**
- c) A 3-phase, star-connected alternator has a line voltage of 11kV. The output of the a.c. generator is 12MVA at a power-factor of 0.85 lagging. Calculate:
- the phase voltage
 - the power output
 - the line current **(10 marks)**
- d) Explain the effect of changing excitation of a 3-phase synchronous motor running with a constant load. **(7 marks)**

Question FOUR

- a) Describe the following parts of a 3-phase transformer tank:
- oil
 - core **(4 marks)**
- b) A delta-star, 3-phase power transformer is rated 11kV/415V, respectively. Calculate the:
- phase voltage in the primary winding
 - phase voltage in the secondary winding **(5 marks)**
- c) With the aid of a labelled diagram, explain how a 3-phase, delta-star transformer can feed:
- THREE** single-phase loads
 - TWO** 3-phase loads **(11 marks)**

Question FIVE

- a) Describe the terms:
- i). planned preventive maintenance
 - ii). breakdown maintenance
- (4 marks)**
- b) Explain the safety procedures to be observed when performing electrical repairs. **(16 marks)**